

**DS-PS102X**  
**Wired External Sounder**

The wired sounder is used to connect to wired control panel, can be controlled by PGM/BELL port from panel. The sounder can alarm up to 105dB sound. The sounder can be used both internal or external, the LED flash and the sounder indication can be configured separately.

- Sound Decibel: 1 meter Single frequency point 110 dBA(Maximum value) Single frequency point 106 dBA(Average value)
- IP55 protective level
- Sound and LED flash indication separately
- Controlled by PGM/BELL port
- Three types of alarm sounds are available: fire alarm, panic alarm, and intrusion alarm.
- Triggered by Positive / Negative
- Tamper Alarm & Cut Wire Alarm

## ▪ Specification

| Hardware features          |   |
|----------------------------|---|
| Tamper-Proof               | Front cover tamper-proof<br>Wall tamper-proof |
| Audio                      |   |
| Sound pressure             | 110dB/1m (Maximum Value)                      |
| Electrical characteristics |   |
| Power supply               | 9 to 16VDC                                    |
| Typical voltage            | 12 VDC  |
| Power consumption          | Maximum current: 180mA@12V DC                 |
| Operation humidity         | 10% ~ 90%                                     |
| Operation temperature      | -20°C ~ +60°C                                 |
| General                    |   |
| IP rate                    | IP55  |
| Dimension(WxHxD)           | 221x215x51mm                                  |
| Shell material             | PC+ABS  |
| Color                      | Red / Blue                                    |
| Weight                     | 475g  |

## ▪ Available Model

DS-PS102X/红色

DS-PS102X/蓝色

# See Far, Go Further



[www.hikvision.com](http://www.hikvision.com)  
[support@hikvision.com](mailto:support@hikvision.com)

