





Superior StreetSiren Plus G3 Jeweller

Wireless siren with advanced sabotage protection and an extended list of compliance certificates.

For outdoor and indoor use.



This is a device of the Superior product line. Only accredited Ajax Systems partners can sell, install, and maintain Superior products.



One device, multiple missions

- An audible alarm to deter intruders and attract attention
- Security state indication to inform users of the system being armed/disarmed
- LED and sound indication of entry/exit delays
- Chime feature to alert users to opening detectors being triggered while the system is disarmed
- After-alarm LED indication to show users and passing patrols if there were any alarms in the system



Superior Jeweller communication technology

- Up to 3,000 m (9,800 ft) of radio communication² in open space
- Enhanced data encryption
- Regular polling to display current device states
- Device authentication to prevent spoofing




Sabotage resistance

- Tamper alarm to inform users and a monitoring company if the tamper button is triggered
- Lock to secure the siren to SmartBracket
- Durable enclosure with IP54 and IK08 protection rating
- Jamming detection
- Frequency hopping to prevent radio interference
- Connection loss detection



Adjustable alerts

- Adjustable¹ alarm volume: from 85 dB to 107 dB
- Adjustable alarm duration: from 3 s to 3 min
- Selectable sound patterns
- Group mode for the siren to respond to events and security mode changes in its assigned group only




System supervision

- Low battery notifications and status display in Ajax apps
- Automatic device self-diagnosis with state report generation
- Notifications in case of malfunctions



Easy installation and setup

- Adding to the system via a QR code
- SmartBracket mounting panel for installation without enclosure disassembly
- Bubble level to check the inclination angle of the mounting during installation
- Remote control and configuration in mobile and desktop Ajax apps
- Installation kit with all necessary fasteners
- Up to 10 years³ of operation on enhanced pre-installed batteries
- Possibility to connect an external 12 V $\overline{=}$ power supply

<p>Compliance with standards</p> <p>EN 50131 (Grade 3) NFA2P (3 shields) INCERT</p> <p>Compatibility with hubs and range extenders</p> <p>For detailed information, scan the QR code or follow the link:</p>  <p>ajax.systems/tools/devices-compatibility/?models=SSP.G3.J</p>	<p>Communication with a hub or range extender</p> <p>Superior Jeweller communication technology</p> <p>Frequency bands 865.0–868.0 MHz 868.0–868.6 MHz 868.7–869.2 MHz 869.4–869.65 MHz</p> <p>Each device supports these four bands</p> <p>Communication range² up to 3,000 m up to 9,800 ft In open space</p>	<p>Alerts</p> <p>Alarm Audible, LED</p> <p>Entry/exit delay Audible, LED</p> <p>Security mode Audible, LED</p> <p>Security state LED</p> <p>Chime feature Audible</p> <p>If the feature is enabled, the siren will make a short beep to indicate that opening detectors have been triggered while the system was disarmed.</p> <p>After-alarm indication LED</p>	<p>Features</p> <p>Alarm volume from 85 dB to 107 dB at a distance of 1 m (3.3 ft) away from the siren Adjusted by a PRO or a user with admin rights in Ajax apps</p> <p>Alarm duration from 3 s to 3 min</p> <p>Siren sound frequency 1,400–1,600 Hz</p>
<p>Power supply</p> <p>Batteries 8 × CR123A (pre-installed)</p> <p>Battery life up to 10 years³</p> <p>Backup optional external 12 V⁼⁼ power supply</p>	<p>Installation</p> <p>Operating temperature –25 °C to +60 °C –13 °F to +140 °F</p> <p>Operating humidity up to 95%</p>	<p>Enclosure</p> <p>Color white, black</p> <p>Dimensions 210 × 210 × 71 mm 8.27" × 8.27" × 2.80"</p> <p>Weight 1,146 g 40 oz</p> <p>Protection class IP54 IK08</p>	<p>Complete set</p> <p>Superior StreetSiren Plus G3 Jeweller 8 × CR123A battery (pre-installed) Installation kit Quick start guide</p>

¹ Measured at a distance of 1 m (3.3 ft) away from the siren.




² Communication range depends on a hub model.

³ Battery life in standby mode. Up to 4.2 years with one 90-second alarm per day.



For detailed information, scan the QR code or follow the link:

<https://ajax.systems/support/devices/superior-streetsiren-plus-g3-jeweller/>

-  support@ajax.systems
-  [@AjaxSystemsSupport_Bot](https://t.me/AjaxSystemsSupport_Bot)
-  ajax.systems